



## Engine Power Chart for Variable Speed Engines.



### ISO3046 Nett Continuous Ratings, kW.

Engine	1000	1100	1200	1300	1400	1500	1600	1700	1800	1900	2000	2100	2200	2300	2400	2500	2600	2700	2800	2900	3000	3200	3400	3600
<b>15D</b>						1.3	1.4	1.6	1.7	1.9	2.0	2.1	2.3	2.4	2.5	2.6	2.8	2.9	3.0	3.0	3.1	3.3	3.4	3.5
<b>15W</b>						1.6	1.8	1.9	2.1	2.3	2.4	2.5	2.7	2.8	2.9	3.1	3.2	3.3	3.4	3.5	3.5	3.7	3.8	3.9
<b>18D</b>						1.5	1.7	1.9	2.1	2.3	2.4	2.6	2.8	2.9	3.1	3.2	3.3	3.5	3.6	3.7	3.8	4.0	4.1	4.2
<b>18W</b>						1.7	1.9	2.1	2.3	2.5	2.7	2.9	3.0	3.2	3.4	3.5	3.7	3.8	3.9	4.0	4.1	4.4	4.5	4.7
<b>43F</b>						4.5	5.2	5.7	6.3	6.8	7.3	7.7	8.2	8.5	8.9	9.1	9.4	9.5	9.7	9.8	9.9			
<b>2CA1</b>			2.6	3.0	3.4	3.8	4.1	4.5	4.9	5.2	5.5	5.9	6.2	6.5	6.8	7.2	7.5	7.7	8.0	8.2	8.5	8.8	9.0	9.1
<b>3CA1</b>			4.2	4.8	5.3	5.9	6.5	7.1	7.7	8.2	8.7	9.3	9.8	10.3	10.8	11.3	11.8	12.2	12.6	13.0	13.3	13.8	14.2	14.7
<b>3CB1</b>			6.2	6.9	7.6	8.4	9.2	10.0	10.8	11.5	12.2	12.8	13.4	14.0	14.6	15.1	15.6	16.0	16.5	16.7	16.8			
<b>3CE1</b>	9.9	10.9	11.9	12.9	13.9	14.8	15.8	16.7	17.6	18.3	19.0	19.6	20.3	20.8	21.4	22.0	22.5	23.0	23.5	23.9	24.2			
<b>4LE1</b>	12.0	13.3	14.7	16.1	17.6	18.9	20.3	21.4	22.6	23.7	24.8	25.8	26.9	27.9	28.8	29.7	30.7							
<b>4LE1T</b>	12.8	15.0	17.1	19.3	21.4	23.4	25.5	27.3	29.1	30.6	32.0	33.3	34.6	35.9	37.2	38.4								
<b>4JJ1T</b>	20.8	23.6	26.4	29.1	31.8	34.5	37.3	39.2	41.1	42.6	44.2	45.3	46.5	47.4	48.4	47.3								
<b>4JJ1X</b>	20.9	26.1	31.2	35.8	40.5	45.4	50.3	55.0	59.7	63.2	66.7	69.0	71.3	73.2	75.2									
<b>4HK1X</b>	41.6	50.9	60.1	68.8	77.5	84.4	91.4	96.6	101.8	107.0	112.2	117.4												
<b>6HK1X</b>	65.1	79.1	93.0	109.3	125.6	135.6	145.7	153.1	160.4	162.4	164.3													

Overload is available on Intermittently rated engines.

Derate in accordance with ISO3046 / SAE J1349.